

TCPWM (PWM mode) example project

2.0

Features

- Project uses TCPWM component with PWM mode configuration
- Indicate line output signal behavior on LED
- LED brightness decremented using terminal count interrupt

General Description

This example project demonstrates the TCPWM component usage in the PWM mode.

Development kit configuration

This example project is designed to run on the CY8CKIT-042 kit from Cypress Semiconductor. A description of the kit, along with more example programs and ordering information, can be found at <http://www.cypress.com/go/cy8ckit-042>.

The project requires configuration settings changes to run on other kits from Cypress Semiconductor. Table 1 is the list of the supported kits. To switch from CY8CKIT-042 to any other kit, change the project's device with the help of Device Selector called from the project's context menu.

Table 1. Development Kits vs Parts

Development Kit	Device
CY8CKIT-042	CY8C4245AXI-483
CY8CKIT-040	CY8C4014LQI-422
CY8CKIT-042-BLE	CY8C4247LQI-BL483
CY8CKIT-044	CY8C4247AZI-M485
CY8CKIT-046	CY8C4248BZI-L489
CY8CKIT-041	CY8C4045AZI-S413 / CY8C4146AZI-S433
CY8CKIT-048	CY8C4A45LQI-483

The pin assignments for the supported kits are in Table 2.

Table 2. Pin Assignment

Pin Name	Development Kit						
	CY8CKIT-042	CY8CKIT-040	CY8CKIT-042 BLE	CY8CKIT-044	CY8CKIT-046	CY8CKIT-041	CY8CKIT-048
LED_GREEN	P0[2]	P1[1]	P3[6]	P2[6]	P5[3]	P2[6]	P2[6]

The following steps should be performed to observe the project operation:

1. Build the project and program the hex file on to the target device.

2. Power cycle the device and observe the results on the green color LED.

Project configuration

The example project consists of the following components: TCPWM, Clock, digital output pin, and Interrupt. The TCPWM is used as the Left align PWM mode. The output pins are used to reflect the line signal output behavior.

Project description

In the project, the TCPWM counts from 0u to 63000u value. The compare value increases by 100u during the terminal count interrupt. When the counter starts, the compare value is 0u; the line output is always 0, so the LED brightness is in high power. After the compare value increases, the duty cycle high state of the line output signal is longer; thus the LED brightness decreases. When the line output is high, the LED brightness is in low power.

Expected results

The green color LED changes its brightness from high to low power lighting (in a cycle).



Cypress Semiconductor
198 Champion Court
San Jose, CA 95134-1709

Phone : 408-943-2600
Fax : 408-943-4730
Website : www.cypress.com

© Cypress Semiconductor Corporation, 2009-2016. The information contained herein is subject to change without notice. Cypress Semiconductor Corporation assumes no responsibility for the use of any circuitry other than circuitry embodied in a Cypress product. Nor does it convey or imply any license under patent or other rights. Cypress products are not warranted nor intended to be used for medical, life support, life saving, critical control or safety applications, unless pursuant to an express written agreement with Cypress. Furthermore, Cypress does not authorize its products for use as critical components in life-support systems where a malfunction or failure may reasonably be expected to result in significant injury to the user. The inclusion of Cypress products in life-support systems application implies that the manufacturer assumes all risk of such use and in doing so indemnifies Cypress against all charges.

PSoC® is a registered trademark, and PSoC Creator™ and Programmable System-on-Chip™ are trademarks of Cypress Semiconductor Corp. All other trademarks or registered trademarks referenced herein are property of the respective corporations.

Any Source Code (software and/or firmware) is owned by Cypress Semiconductor Corporation (Cypress) and is protected by and subject to worldwide patent protection (United States and foreign), United States copyright laws and international treaty provisions. Cypress hereby grants to licensee a personal, non-exclusive, non-transferable license to copy, use, modify, create derivative works of, and compile the Cypress Source Code and derivative works for the sole purpose of creating custom software and or firmware in support of licensee product to be used only in conjunction with a Cypress integrated circuit as specified in the applicable agreement. Any reproduction, modification, translation, compilation, or representation of this Source Code except as specified above is prohibited without the express written permission of Cypress.

Disclaimer: CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS MATERIAL, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Cypress reserves the right to make changes without further notice to the materials described herein. Cypress does not assume any liability arising out of the application or use of any product or circuit described herein. Cypress does not authorize its products for use as critical components in life-support systems where a malfunction or failure may reasonably be expected to result in significant injury to the user. The inclusion of Cypress' product in a life-support systems application implies that the manufacturer assumes all risk of such use and in doing so indemnifies Cypress against all charges.

Use may be limited by and subject to the applicable Cypress software license agreement.

